

## ENGLISH

Thank you for selecting the ProTac® 2AA-X multi-fuel, personal carry tactical flashlight. As with any professional tool, reasonable care and maintenance of this product will provide years of dependable service. Please read this manual before using your ProTac®.

SAVE THESE INSTRUCTIONS. This guide contains important safety and operating instructions for your ProTac®.

**CAUTION** STROBE MODE MAY CAUSE SEIZURES IN PERSONS WITH PHOTOSENSITIVE EPILEPSY.

**CAUTION** LED RADIATION (RG-2). DO NOT STARE INTO BEAM. MAY BE HARMFUL TO EYES. PER IEC 62471 Ed 1.0:2006-07.

**WARNING** RISK OF INJURY. THE USE OF SUBSTANDARD OR AFTER-MARKET COMPONENTS, MODIFICATIONS TO THE ORIGINAL PARTS, OR USE OF THIS FLASHLIGHT WITH ANY INCOMPATIBLE PRODUCT MAY VOID WARRANTY AND COULD LEAD TO PRODUCT FAILURE OR PERSONAL INJURY.

### BATTERY SAFETY

**CAUTION** EXPLOSION RISK, BURN, AND FIRE HAZARD. DO NOT DISASSEMBLE, CRUSH, SHORT CIRCUIT, HEAT ABOVE 140°F (60°C), OR DISCARD IN FIRE. USE ONLY WITH THE SPECIFIED STREAMLIGHT PRODUCTS. KEEP AWAY FROM CHILDREN. BATTERY MUST BE RECYCLED OR DISPOSED OF PROPERLY.

**NOTICE** This product is designed to use two AA batteries or one Streamlight #940215 protected Li-ion rechargeable battery pack.

The rechargeable battery contained in this product is recyclable. At the end of its useful life, under various country and state laws, it may be illegal to dispose of this battery in the municipal solid waste stream. Check with your local solid waste officials for details in your area for recycling options or proper disposal (In USA: RBRC).

### BATTERY INSTALLATION/REMOVAL

At the end of battery life, the switch may appear intermittent or non-functional. Replacing or recharging the batteries will restore normal operation.

1. Unscrew the tailcap and remove expired batteries.
2. Install new AA batteries or recharged Li-ion battery positive end first. Polarity is marked on the inside of the body.
3. Replace tailcap.

### PROTAC® 2AA-X LI-ION BATTERY CHARGING

**NOTICE** Fully charge batteries before first use.

The ProTac® 2AA-X USB model ships with one Li-ion rechargeable battery with integrated charge port.

To charge the battery, insert the USB-C plug into the connector near the positive end of the battery. The battery may be left plugged into a USB-C cable continuously, there is no danger of overcharging.

### LED Charge Indicator

- Charging...Red LED is on.
  - Charged...Green LED is on.
- The charge time is approximately 4 hours.

### GENERAL OPERATION

The ProTac® 2AA-X features a programmable switch with momentary operation (light press or tap) and constant on operation (press until click).

- High: Tap and hold; click to lock on; click again for off.
- Strobe: Fast double-tap (within a half second) and hold; click to lock on; click again for off.
- Low: Fast triple-tap (within a half second per tap) and hold; click to lock on; click again for off.

### Accessing Other Programs

The ProTac® 2AA-X features a TEN-TAP® programmable switch allowing the user to select one of two different programs. To change to the next program, starting from the "Off" position, tap the switch rapidly 9 times (within 0.4 seconds per tap) and hold it down the 10th time. Continue holding the switch until the light turns off (approximately 1 second), then release the switch.

Available programs are High-Strobe-Low (Factory Default), High Only, or Low-High.

### MAINTENANCE

It is important to keep the tailcap O-ring clean and free of debris.

### PRODUCT USE

Streamlight flashlights are intended for use as high intensity, heavy duty, and portable light sources. Use of Streamlight flashlights for any purpose other than as light sources is specifically discouraged by the manufacturer. Streamlight specifically disclaims liability for other than recommended use.

**NOTICE** Be sure to use only genuine Streamlight replacement parts to ensure product safety. Substitution may invalidate the product approval. Do not try to repair the unit yourself. Send to a qualified service facility or return it to the factory.

### Streamlight Limited Lifetime Warranty

Streamlight warrants this product to be free of defects for a lifetime of use except for batteries and bulbs, abuse, and normal wear. We will repair, replace, or refund the purchase price of this product should we determine it to be defective. This limited lifetime warranty also excludes rechargeable batteries, chargers, switches, and electronics which have a 2-year warranty with proof of purchase. **THIS IS THE ONLY WARRANTY, EXPRESSED OR IMPLIED, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES ARE EXPRESSLY DISCLAIMED EXCEPT WHERE SUCH LIMITATION IS PROHIBITED BY LAW.** You may have other specific legal rights which vary by jurisdiction.

Go to [www.streamlight.com/support](http://www.streamlight.com/support) for a complete copy of the warranty. To regis-

ter your product, go to [www.streamlight.com](http://www.streamlight.com) (Online Product Registration). Retain your receipt or any proof of purchase.

### SERVICE OPTIONS

The ProTac® series contains few or no user-serviceable parts.

For service options, go to [www.streamlight.com/support/service](http://www.streamlight.com/support/service) and complete the Online Service Request for factory service or to find the location of an authorized Streamlight repair center near you.

### Or contact:

Customer Service  
STREAMLIGHT, INC.  
30 Eagleville Road  
Suite 100  
Eagleville, PA U.S.A. 19403-3996  
Phone: (800) 523-7488 Toll-Free / +1 (610) 631-0600  
Fax: (800) 220-7007 / +1 (610) 631-0712



# PROTAC® 2AA-X PROTAC® 2AA-X USB

available at **BrightGuy.com**

**IMPORTANT:**  
FULLY CHARGE BATTERY  
BEFORE FIRST USE.

**IMPORTANT :**  
CHARGER COMPLÈTEMENT LA PILE  
AVANT LA PREMIÈRE UTILISATION.

Caution: LED Radiation (RG-2) -  
Do not stare into beam.  
May be harmful to eyes.

Attention : Rayonnement LED (RG-2) -  
Ne pas regarder dans le faisceau.  
Susceptible d'endommager les yeux.

**IMPORTANTE:**  
CARGUE LA PILA COMPLETAMENTE  
ANTES DE USARLA POR PRIMERA VEZ.

**WICHTIG:**  
LADEN SIE DIE BATTERIE VOR DEM  
ERSTEN GEBRAUCH VOLL AUF.

Precaución: Radiación de LED (RG-2) -  
No mire directamente al haz.  
Podría dañar su vista.

Achtung: LED-Strahlung (RG-2) -  
Nicht direkt in den Lichtstrahl schauen.  
Augenschädigung möglich.

EU Authorized Representative:  
Falcon Logistics B.V., Hoeksteen 26 F,  
2132 MS Hoofddorp, Netherlands  
For compliance information, please visit  
[www.streamlight.com/compliance](http://www.streamlight.com/compliance)

